



MINI TOUCH

touch-dimmer switch

Code	1772810
Input	24VDC
Output	24VDC
Power	max 36W
Wiring IN	2000mm Micro24 male
Wiring OUT	2000mm 10x Micro24 female
Finish	aluminium



MINI TOUCH ACCESSORIES

M24|M12 adapter cable set

Code	4015500/S
Wiring IN	100mm M24F M12M
Wiring OUT	150mm 10xM12F M24M



MINI TOUCH is a touch-dimmer switch that turns ON and Off and adjusts (5-100%) the brightness of the luminaires connected to it. The ON/Off function operates in soft mode, while the brightness adjustment is saved, with the maximum brightness indicated by a brief flash of the luminaires. The luminaire features a built-in blue indicator light ring that turns on when it is off.



MINI TOUCH is designed for installation on surfaces such as wood, plastic, and other non-metallic materials. The “activation” area corresponds to the central surface of the luminaire.



It is therefore advisable to avoid using MINI TOUCH on metallic surfaces, electrically conductive materials, or near heat sources or electromagnetic fields, which could alter or compromise its functioning. Do not connect the MINI TOUCH power supply to a mains wall switch. For more details, please refer to the instruction manual.

MINI TOUCH

touch-dimmer switch



MINI TOUCH is a touch-dimmer switch for controlling single-colour LED luminaires @24VDC, activated by direct finger contact with the surface of the appliance. Quickly tapping on the “activation” area turns the luminaires ON and Off, while holding the button down allows you to adjust the brightness (5-100%) of all the luminaires connected to MINI TOUCH. The appliance is supplied with a 2000mm power cable and Micro24 male connector, a 2000mm output cable and Micro24 female connector, and a distributor with 10 Micro24 female slots. To use MINI TOUCH for controlling single-colour LED luminaires @12VDC (max 18W), an adapter cable set that configures the luminaire with the Micro12 connection system is available. Power supply not included, to be ordered separately.